

Party Amarillo Generator

FOR SAFETY:

1. Caution: Do not use the generator indoors. It is a carbon monoxide hazard.
2. Place the generator at least 15 feet from the blowers so toxic fumes are not sucked into the unit.
3. Always keep children away from the generator.
4. Keep the generator dry. Do not touch it with wet hands. Do not use in wet conditions.
5. The muffler will be hot during and after operation. Use caution when handling.
6. Stop the generator before adding fuel.
7. Do not store the gasoline by the generator.

TO START THE GENERATOR:

1. The generator must be operated and transported in a level position.
2. Fill the generator with unleaded gasoline only. Do NOT use an oil gas mixture.
3. Check oil to see that it is at the full position. The generator will automatically shut down if the oil level is too low. Add oil if needed. The oil required is SAE 30.
4. Make sure all electrical loads are disconnected from the generator before starting.
5. Turn the engine switch to the “on” position.
6. Turn on the fuel switch.
7. Engage the carburetor choke
8. Pull the recoil starter.
9. Once the engine starts move the choke lever to the “run” position.
10. Always keep the circuit breakers in the “on” position.

TO STOP THE GENERATOR:

1. Remove all electrical loads from the generator before turning it off.
2. To stop the generator, turn the engine switch to the “off” position.
3. Use caution because the generator and muffler will be hot.